
# CZH-LABS.com Electronics-Salon

# Passive 5 Amp SPST-NO Slim Power Relay Module

# Model: D-1302 Series





#### Features:

- 1, Original Panasonic APAN31xx relay and PA1a-PS relay socket, with removal key, easy to replace pluggable relay. Relay switch type SPST-NO(when the relay no action switch status off). Switching current up to 5Amp/250V or 5Amp/30VDC.
- 2, Users can flexibly configured control signal mode according to controllers output, can support <u>Common Positive</u>(for <u>NPN / Sink</u> output controllers) and <u>Common Negative</u>(for <u>PNP/Source</u> output controllers). LED indicator for each relay channel. Relay coil protection by means of a freewheeling diode.
- 3, Operating voltage DC 5V / 12V / 24V versions selectable. Relay number 4 / 8 / 16 / 24 / 32 channels to selectable.
- 4, High quality terminal block: Pitch 5.0mm/0.197", Wire range 28AWG ~ 12AWG / 2.5mm square, Strip length 7mm. Screws M2.5,steel,Cr3+ Zn plated. Pin header and Cage Brass.
- 5, Screw mount or DIN rail mount types selectable. DIN rail mount carrier: High quality Taiwan DINKLE fireproof nylon material DIN rail mount carrier (not China low quality carrier), can support width 35mm / 32mm / 15mm rail. FR-4 fiber glass dual layers PCB.

elay Channel Operating Voltage		Screw Hole Mount	DIN Rail Mount	
4	DC5V	MD-D1302/5V-1	MD-D1043T5V/4-1	
	DC12V	MD-D1302/12V-1	MD-D1043T12V/4-1	
	DC24V	MD-D1302/24V-1	MD-D1043T24V/4-1	
8	DC5V	Х	MD-D1043T5V/8-1	
	DC12V	Х	MD-D1043T12V/8-1	
	DC24V	Х	MD-D1043T24V/8-1	
16	DC5V	Х	MD-D1043T5V/16-1	
	DC12V	Х	MD-D1043T12V/16-1	
	DC24V	Х	MD-D1043T24V/16-1	
24	DC5V	Х	MD-D1043T5V/24-1	
	DC12V	Х	MD-D1043T12V/24-1	
	DC24V	Х	MD-D1043T24V/24-1	
32	DC5V	Х	MD-D1043T5V/32-1	
	DC12V	Х	MD-D1043T12V/32-1	
	DC24V	Х	MD-D1043T24V/32-1	

## **Passive SPST-NO Slim Relay Module Version List**

#### **Electrical Parameters:**

Relay Type:	5V version: Panasonic APAN3105 12V version: Panasonic APAN3112		
	24V version: Panasonic APAN3124		
Action Voltage:	5V version: DC 4.5 ~ 6V		
	12V version: DC 9.7 ~ 15V		
	24V version: DC 18.7 ~ 29V		
Release Voltage:	5V version: DC 0 ~ 0.7V		
	12V version: DC 0 ~ 1.0V		
	24V version: DC 0 ~ 1.5V		
Action Current:	5V version: 23mA (one channel).		
	12V version: 11mA (one channel).		
	24V version: 7mA (one channel).		

#### Output:


xNO terminal position: each "NO" position maximum current: 5Amp, 250VAC/30VDC. Cx terminal position: each "C" position maximum current: 16Amp.

Terminal Block: Wire range: 26 ~ 12AWG / 2.5mm<sup>2</sup>, Strip length: 7mm, Screw: Metric slot M2.


#### SCHEMATIC CHANNEL **OUTPUT** INPUT NO. SCREW SCREW CONNECTOR RELAY CONTROL CIRCUIT UINT CONNECTOR TERMINAL TERMINAL -O COM C10--O IN1 INOO--OIN2 2NOO-4 -O IN3 3NOO--OIN4 4NOO--O COM

### Schematic:


**4 Channel Versions** 



#### **Dimensions:**



4 / 8 / 16 / 24 / 32 Channel DIN Rail Mount Versions



CHANNEL NO	). 32	24	16	8	4
L	282mm	212mm	142mm	72mm	42mm